



## O-BOX®

O-Box® presents a cylindrical aluminium box system that will add style and elegance to your space. Its stainless steel components are very resistant to weather which makes it ideal for outdoor installations. It also includes brackets to attach the box system to the ceiling or wall, being able to adapt to any installation needed.



### AVAILABLE COMPONENT COLORS



Black



Metallic grey



Stainless steel grata



White

### OPERATING SYSTEM



Chain



Crank



Motor

### MAXIMUM WIDTH

212" x 39"

### MAXIMUM HEIGHT

78" x 236" (indoor installation)

181" x 157" (outdoor installation)

 Check 'Fabric Limits' in ProArea.

# BOX SYSTEMS - O-BOX®

## Strong and simple mounting

Bandalux has developed stronger idle ends to deliver benchmark endurance and reliability. It contains a solid system with high quality bearings that provides a perfect, smooth and silent (motion) rotation. It can be easily set up by a simple one hand move thanks to its components design.



## Smoothen and silent motorization

All Bandalux motorization products include a brand new, hybrid technology driving wheel specifically designed by us to minimize noise and vibration.



## Level by level installation

Two or more O-Box® can be installed at different heights with only one support and a stainless steel rod.



## Easy maintenance access

The fabric roll can be accessed without the need of uninstalling the system, making maintenance easy.



## Stainless steel components

The rods, tensioners and cable are made of stainless steel to ensure long-lasting outdoor appliance.



## Smart brackets

The two-piece bracket has been designed to ensure an easy shade installation. The brackets allow you to select the optimal installation position.

Wall short bracket



Wall long bracket



Ceiling bracket



## Multiple guide and special options

Specially designed pieces for each type of side guide.

Rod guide



Cable guide



Special fixing configurations



## Safety protection for children

In compliance with the updated child safety standard (ANSI/WCMA A100.1-2022), Bandalux supplies an improved Chain/Cord Tension Device by default.

This device is designed to eliminate free hanging cords and connectors in order to be fully tensioned and fixed to the wall with the aim of preventing children from getting entangled in it.

### Features of the new Child Safety Device:

- Easy device assembly.
- Quick installation.
- Smooth and reliable performance.



# BOX SYSTEMS - O-BOX® 4

## OPTIONS

### Standard configuration

#### Colors



By default, Bandalux will provide the O-Box® 4 in white unless a different color is indicated on the order form or eBa.

#### Chain operated



#### Ø1 3/16" Round fabric wrap bottom hembar



⚠ Fabrics not compatible with hidden bottom hembars will be served with Slim 35 bottom hembar.

#### Chain Tension Device



### Optional configuration

#### BOTTOM HEMBARS



##### Slim 35




##### Ø1 9/16" Round fabric wrap

⚠ Only available for Polyscreen® and blackout fabrics except for: Polyscreen® 314/473/473 Metal/475/Silken; Bimini BO; South Beach BO.



##### Metallic chain



##### Fabric customization

⚠ Only available for indoor installation.

### Reduced effort for chain-operated systems



#### Redux® system

Bandalux recommends REDUX® SYSTEM: Chain clutch mechanism that **reduces up to 35% of the shade's weight**.

⚠ Redux® systems do not include a limit stop (endless chain). / The chain route length is three times the shade height.



#### Spring assist

Recommended for shades larger than 6 sq yds:

142" x 157" shade example:


- Effort without spring assist = 10.6 lbs
- Effort with spring assist = 4.9 lbs

### Operating system options

#### CRANK



##### Fixed



##### Removable

## Operating system options

### MOTOR

|   |                         | ACCESSORIES                           |                               |                              |                             |                            |                                 |
|---|-------------------------|---------------------------------------|-------------------------------|------------------------------|-----------------------------|----------------------------|---------------------------------|
|   |                         | MOTOR <sup>(1)</sup>                  | Single channel remote control | Multi channel remote control | Wirefree wall switch        | Charger for battery motors | Wifi RTS interface              |
| RADIO   | Somfy® RTS              | SONESSE 40 4/36 120Vac                | Situo 1<br>Ref. 06700604C     | Situo 5<br>Ref. 06700606C    | RTS 5 CH<br>Ref. 06705020   | --                         | Tahoma<br>Ref. 06700660U        |
|   |                         | SONESSE 50 6/32 120Vac                |                               |                              |                             |                            |                                 |
|   |                         | ULTRA QUIET 50 6/24 120Vac            |                               |                              |                             |                            |                                 |
| LOW VOLTAGE RECHARGEABLE BATTERY <sup>(2)</sup> | Vertilux                | QUIET 40 6/33 120Vac                  | 1 CH<br>Ref. 18510110B        | 6 CH<br>Ref. 18510120B       | 6 CH<br>Ref. 18500150       | --                         | VTi Smart Hub<br>Ref. 12132001  |
|   |                         | ULTRA QUIET 50 6/28 120Vac            |                               |                              |                             |                            |                                 |
|   | Somfy® RTS              | SONESSE 40 RECHARGEABLE 3/28 WF 12Vdc | Situo 1<br>Ref. 06700604C     | Situo 5<br>Ref. 06700606C    | RTS 5 CH<br>Ref. 06705020   | Charger<br>Ref. 05499582   | Cable ext. 96"<br>Ref. 05499583 |
| Rollease Automate                               | Rollease Automate       | LI-ION 40 3.0 Not quiet 12Vdc         | 1 CH<br>Ref. 05499930         | 15 CH<br>Ref. 05499935       | 5 CH<br>Ref. 05499990       | Charger<br>Ref. 05499920   | Cable ext. 96"<br>Ref. 05499921 |
|   |                         | LI-ION 50 3.0 12Vdc                   |                               |                              |                             |                            |                                 |
|   |                         | LI-ION 50 10.0 12Vdc                  |                               |                              |                             |                            |                                 |
| Bandalux <sup>(3)</sup>                         | Bandalux <sup>(3)</sup> | RECHARGEABLE BI 40 3/28 12Vdc         | 1 CH<br>Ref. 06701100B        | 15 CH<br>Ref. 06701110B      | 15 CH<br>Ref. 06701180B     | Charger<br>Ref. 06701210   | Cable ext. 8FT<br>Ref. 06701250 |
|   |                         | RECHARGEABLE BI 50 3/28 12Vdc         |                               |                              |                             |                            |                                 |
|   |                         | RECHARGEABLE BI 50 10/9 12Vdc         |                               |                              |                             |                            |                                 |
|   | Vertilux                | RECHARGEABLE 40 6/18 12Vdc            | 1 CH<br>Ref. 18510110B        | 6CH<br>Ref. 18510120B        | Radio 6 CH<br>Ref. 18500150 | Charger<br>Ref. 05499412   | --                              |
|   |                         |                                       |                               |                              |                             |                            | VTi Smart Hub<br>Ref. 12132001  |

<sup>(1)</sup> To guarantee a proper functionality Bandalux will provide the appropriate motor model according to the shade size. / Price for rechargeable battery motors includes 1 charger and 1 cable extender per order. / Motor only compatible for indoor installation. / Please refer to your sales representative for Bandalux motor delivery deadlines.

## Cable guides

### CABLE GUIDES (indoor/outdoor)

#### Ø<sup>3</sup>/<sub>16</sub>" Stainless cable guide

Wall fixing



Floor fixing



#### Ø<sup>3</sup>/<sub>16</sub>" Stainless reinforced cable guide

Floor fixing



### ROD GUIDES (indoor/outdoor)

#### Wall fixing



#### Floor fixing



#### Ø<sup>3</sup>/<sub>8</sub>" Stainless rod guide

|               |     |
|---------------|-----|
| Ceiling/Floor | VTS |
| Ceiling/Wall  | VTP |
| Wall/Floor    | VPS |
| Wall/Wall     | VPP |

<sup>(1)</sup> Max. height: 118 1/8".

## Additional brackets

### Wall short bracket



### Wall long bracket



### Ceiling bracket



|               |    |
|---------------|----|
| Ceiling/Floor | TS |
| Ceiling/Wall  | TP |
| Wall/Floor    | PS |
| Wall/Wall     | PP |

|               |     |
|---------------|-----|
| Ceiling/Floor | BTS |
| Wall/Floor    | BPS |

# BOX SYSTEMS - O-BOX® 5

## OPTIONS

### Standard configuration

#### Colors



By default, Bandalux will provide the O-Box® 5 in white unless a different color is indicated on the order form or eBa.

#### Ø1³/₁₆" Round fabric wrap bottom hembar



⚠ Fabrics not compatible with hidden bottom hembars will be served with Slim 35 bottom hembar.

### Optional configuration

#### Slim 35 bottom hembar



#### Ø1⁹/₁₆" Round fabric wrap bottom hembar




⚠ Only available for Polyscreen® and blackout fabrics except for: Polyscreen® 314/473/473 Metal/475/Silken; Bimini BO; South Beach BO.

### Operating system options

#### CRANK



#### Fixed



#### Removable

#### MOTOR

| MOTOR <sup>(1)</sup>                            |                     |  | ACCESSORIES                   |                              |                        |                            |                              |                             |
|---|---------------------|--|-------------------------------|------------------------------|------------------------|----------------------------|------------------------------|-----------------------------|
|   |                     |  | Single channel remote control | Multi channel remote control | Wirefree wall switch   | Charger for battery motors | Battery motor cable extender | Wifi RTS interface          |
| RADIO   | Somfy® RTS          | SONESSE 50 6/32 <sup>(4)</sup> 120Vac  | Situo 1 Ref. 06700604C        | Situo 5 Ref. 06700606C       | RTS 5 CH Ref. 06705020 | --                         | --                           | Tahoma Ref. 06700660U       |
|   |                     | SONESSE 50 10/32 <sup>(4)</sup> 120Vac |                               |                              |                        |                            |                              |                             |
|   |                     | ULTRA QUIET 50 6/24 120Vac             |                               |                              |                        |                            |                              |                             |
| LOW VOLTAGE RECHARGEABLE BATTERY <sup>(2)</sup> | Vertilux            | ULTRA QUIET 50 6/28 120Vac             | 1 CH Ref. 18510110B           | 6 CH Ref. 18510120B          | 6 CH Ref. 18500150     | --                         | --                           | VTi Smart Hub Ref. 12132001 |
|   | Rollelease Automate | LI-ION 50 3.0 12Vdc                    | 1 CH Ref. 05499930            | 15 CH Ref. 05499935          | 5 CH Ref. 05499990     | Charger Ref. 05499920      | Cable ext. 96" Ref. 05499921 | Pulse Hub Ref. 05499971     |
|   |                     | LI-ION 50 10.0 12Vdc                   |                               |                              |                        |                            |                              |                             |
| Bandalux <sup>(3)</sup>                         |                     | RECHARGEABLE BI 50 3/28 12Vdc          | 1 CH Ref. 06701100B           | 15 CH Ref. 06701110B         | 15 CH Ref. 06701180B   | Charger Ref. 06701210      | Cable ext. 8FT Ref. 06701250 | --                          |
|   |                     | RECHARGEABLE BI 50 10/9 12Vdc          |                               |                              |                        |                            |                              |                             |

⚠ To guarantee a proper functionality Bandalux will provide the appropriate motor model according to the shade size. / Price for rechargeable battery motors includes 1 charger and 1 cable extender per order. / Motor only compatible for indoor installation. / Please refer to your sales representative for Bandalux motor delivery deadlines.

## Cable guides

### CABLE GUIDES (indoor/outdoor)

#### Ø<sup>3</sup>/<sub>16</sub>" Stainless cable guide

Wall  
fixingFloor  
fixing

#### Ø<sup>3</sup>/<sub>16</sub>" Stainless reinforced cable guide

Floor  
fixing

Ceiling/Floor

TS

Ceiling/Wall

TP

Wall/Floor

PS

Wall/Wall

PP

! This part does not allow to install the shade tight to the wall or columns. O-Box® 5 shades must be ordered 1" narrower.

Ceiling/Floor


BTS

Wall/Floor

BPS

### ROD GUIDES (indoor/outdoor)

#### Ø<sup>3</sup>/<sub>8</sub>" Stainless rod guide

Wall  
fixingFloor  
fixing

|               |     |
|---------------|-----|
| Ceiling/Floor | VTS |
| Ceiling/Wall  | VTP |
| Wall/Floor    | VPS |
| Wall/Wall     | VPP |

! Max. height: 118 1/8".

#### Ø<sup>1</sup>/<sub>2</sub>" Stainless rod guide adjustable fixing with stainless rod guide



|               |     |
|---------------|-----|
| Ceiling/Floor | RTS |
| Ceiling/Wall  | RTP |
| Wall/Floor    | RPS |
| Wall/Wall     | RPP |

! Only compatible with Ø19/16" Round fabric wrap bottom hembar.

## SPECIAL CONFIGURATION



#### Ø<sup>1</sup>/<sub>2</sub>" Stainless rod guide adjustable fixing with stainless cable guide

|               |     |
|---------------|-----|
| Ceiling/Floor | CTS |
| Ceiling/Wall  | CTP |
| Wall/Floor    | CPS |
| Wall/Wall     | CPP |

## Additional brackets

### Wall short bracket



### Wall long bracket




### Ceiling bracket



## Other options

### Fabric customization



! Only available for indoor installation.

# BOX SYSTEMS - O-BOX®

## TECHNICAL DATA


### Operating systems and minimum shade width

| Operating system | Motor name                                     | Sound Level (dBa) | Ø (mm) | Nm | r.p.m.   | IP    | Requires charger/transformer | Motor Vdc/Vac | Minimum shade width  |                      |
|------------------|--|-------------------|--------|----|----------|-------|------------------------------|---------------|----------------------|----------------------|
|                  |  |                   |        |    |          |       |                              |               | O-BOX® 4             | O-BOX® 5             |
| CHAIN            | --   | --                | --     | -- | --       | --    | --                           | --            | 15 $\frac{3}{4}$ "   | --                   |
| CRANK            | --   | --                | --     | -- | --       | --    | --                           | --            | 15 $\frac{3}{4}$ "   | 15 $\frac{3}{4}$ "   |
| SOMFY®           | SONESSE 40 4/36 <sup>(3)</sup>                 | 42                | 40     | 4  | 36       | 44    | No                           | 120 Vac       | 24 $\frac{7}{16}$ "  | --                   |
|                  | SONESSE 40 RECHARGEABLE 3/28 WF <sup>(3)</sup> | 44                | 40     | 3  | 10/28    | 30    | Yes                          | 12 Vdc        | 29 $\frac{15}{16}$ " | --                   |
|                  | SONESSE 50 6/32 <sup>(3)</sup>                 | $\leq$ 44         | 50     | 6  | 32       | 31    | No                           | 120 Vac       | 30 $\frac{9}{16}$ "  | 30 $\frac{9}{16}$ "  |
|                  | SONESSE 50 10/32 <sup>(3)</sup>                | $\leq$ 45         | 50     | 10 | 32       | 44    | No                           | 120 Vac       | --                   | 30 $\frac{9}{16}$ "  |
|                  | ULTRA QUIET 50 6/24                            | $\leq$ 38         | 50     | 6  | 24       | 31    | No                           | 120 Vac       | 36 $\frac{3}{4}$ "   | 36 $\frac{3}{4}$ "   |
| RELEASE AUTOMATE | LI-ION 40 3.0                                  | 53                | 35     | 3  | 28/24/20 | 44    | Yes                          | 12 Vdc        | 37 $\frac{11}{16}$ " | --                   |
|                  | LI-ION 50 3.0                                  | 40                | 45     | 3  | 28/24/20 | 44    | Yes                          | 12 Vdc        | 36 $\frac{3}{8}$ "   | 36 $\frac{3}{8}$ "   |
|                  | LI-ION 50 10.0                                 | 42                | 45     | 10 | 9/8/6    | 44    | Yes                          | 12 Vdc        | 36 $\frac{3}{8}$ "   | 36 $\frac{3}{8}$ "   |
| BANDALUX         | RECHARGEABLE BI 40 3/28                        | 53                | 40     | 3  | 28/24/20 | 44    | Yes                          | 12 Vdc        | 31 $\frac{9}{16}$ "  | --                   |
|                  | RECHARGEABLE BI 50 3/28                        | 40                | 50     | 3  | 28/24/20 | 44    | Yes                          | 12 Vdc        | 35 $\frac{11}{16}$ " | 35 $\frac{11}{16}$ " |
|                  | RECHARGEABLE BI 50 10/9                        | 42                | 50     | 10 | 9/8/6    | 44    | Yes                          | 12 Vdc        | 35 $\frac{11}{16}$ " | 35 $\frac{11}{16}$ " |
| VERTILUX         | RECHARGEABLE 40 6/18                           | N/I/A             | 35     | 6  | 18       | N/I/A | Yes                          | 12 Vdc        | 35"                  | --                   |
|                  | QUIET 40 6/33                                  | N/I/A             | 40     | 6  | 33       | 44    | No                           | 120 Vac       | 28 $\frac{5}{16}$ "  | --                   |
|                  | ULTRA QUIET 50 6/28                            | N/I/A             | 50     | 6  | 28       | N/I/A | No                           | 120 Vac       | 31 $\frac{3}{16}$ "  | 31 $\frac{3}{16}$ "  |

**●** To guarantee proper functioning, Bandalux will provide the appropriate motor model according to the shade size. / N/I/A: No info available. / Motor only compatible for indoor installation.

### Controls height

#### CHAIN




Minimum calculation for hc: H x 0.90

| Estimate example |                    |
|------------------|--------------------|
| Shade height H   | Controls height hc |
| 40"              | 36"                |
| 80"              | 72"                |
| 160"             | 144"               |

**●** The controls height will always be measured from the highest part of the shade (bracket upper part) to the lowest part of the operating system.


#### CRANK




#### hc - (Std.) Standard crank heights

- 39 $\frac{1}{4}$ "
- 47 $\frac{1}{4}$ "
- 55 $\frac{1}{4}$ "
- 63"
- 70 $\frac{3}{4}$ "
- 78 $\frac{3}{4}$ "
- 86 $\frac{1}{2}$ "
- 94 $\frac{1}{2}$ "
- 102 $\frac{1}{4}$ "
- 110 $\frac{1}{4}$ "
- 118 $\frac{1}{4}$ "


**●** If the controls height does not correspond to any of this table sizes, the manufacturing will always be based on the immediate lower size. / The controls height will always be measured from the highest part of the shade (upper part of the bracket) to the lowest part of the crank when not extended (according to diagram). / Measurement with extended crank: add 51 $\frac{1}{2}$ ". If other controls height is required, please indicate on the order form or eBa.

**Box system sizes**


Ceiling bracket




Wall short bracket




Wall long bracket

ø12 rod guide  
adjustable fixing


|          | A                  | B                 | A                 | B                   | A                  | B                   | A                  | B                 |
|----------|--------------------|-------------------|-------------------|---------------------|--------------------|---------------------|--------------------|-------------------|
| O-BOX® 4 | 4 $\frac{7}{16}$ " | 5"                | 5"                | 4 $\frac{5}{8}$ "   | 6 $\frac{1}{2}$ "  | 4 $\frac{5}{8}$ "   | --                 | --                |
| O-BOX® 5 | 5 $\frac{7}{8}$ "  | 6 $\frac{3}{8}$ " | 6 $\frac{3}{8}$ " | 5 $\frac{13}{16}$ " | 7 $\frac{7}{16}$ " | 5 $\frac{13}{16}$ " | 6 $\frac{7}{16}$ " | 7 $\frac{7}{8}$ " |

**Bottom hembars and retraction heights**

HIDDEN BOTTOM HEMBARS




VISIBLE BOTTOM HEMBARS



ø13/16" Round fabric wrap



ø1 1/16" Round fabric wrap



Slim 35

|                      | A                  | B                 | A                   | B                  | A                 | B                 |
|----------------------|--------------------|-------------------|---------------------|--------------------|-------------------|-------------------|
| O-BOX® 4             | 6 $\frac{7}{16}$ " | 5 $\frac{3}{4}$ " | 6 $\frac{13}{16}$ " | 6 $\frac{3}{16}$ " | 6 $\frac{1}{2}$ " | 5 $\frac{7}{8}$ " |
| O-BOX® 5             | 7 $\frac{3}{4}$ "  | 7 $\frac{1}{8}$ " | 8 $\frac{1}{8}$ "   | 7 $\frac{9}{16}$ " | 7 $\frac{7}{8}$ " | 7 $\frac{1}{4}$ " |
| WITHOUT SIDE GUIDES  | ✓                  |                   | ✓                   |                    | ✓                 |                   |
| WITH CABLE GUIDE     | ✓                  |                   | ✓                   |                    | ✗                 |                   |
| WITH ø3/8" ROD GUIDE | ✓                  |                   | ✓                   |                    | ✗                 |                   |
| WITH ø1/2" ROD GUIDE | ✗                  |                   | ✓                   |                    | ✗                 |                   |

# BOX SYSTEMS - O-BOX®

## TECHNICAL DATA

### Space between bracket and fabric (GAP)



### Production tolerance



|          | without side guides |      | with cable guides                 |                                  | with rod guides                   |                                  | Rod guide fixing with cable guide |                                 | Rod guide fixing with rod guide |                                   |
|----------|---------------------|------|-----------------------------------|----------------------------------|-----------------------------------|----------------------------------|-----------------------------------|---------------------------------|---------------------------------|-----------------------------------|
|          | w1                  | w2   | w1                                | w2                               | w1                                | w2                               | w1                                | w2                              | w1                              | w2                                |
| O-BOX® 4 | CHAIN               | 7/8" | 1 <sup>3</sup> / <sub>16</sub> "  | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> "  | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> "  | --                              | --                              | --                                |
|          | CRANK               | 7/8" | 1 <sup>7</sup> / <sub>16</sub> "  | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> "  | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> "  | --                              | --                              | --                                |
|          | 12Vdc MOTOR         | 7/8" | 1 <sup>13</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>13</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>13</sup> / <sub>16</sub> " | --                              | --                              | --                                |
|          | 120Vac MOTOR        | 7/8" | 1 <sup>13</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>13</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>13</sup> / <sub>16</sub> " | --                              | --                              | --                                |
| O-BOX® 5 | CRANK               | 7/8" | 1 <sup>7</sup> / <sub>16</sub> "  | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> "  | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> "  | 2 <sup>7</sup> / <sub>8</sub> " | 2 <sup>7</sup> / <sub>8</sub> " | 2 <sup>15</sup> / <sub>16</sub> " |
|          | 12Vdc MOTOR         | 7/8" | 1 <sup>13</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>13</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>13</sup> / <sub>16</sub> " | 2 <sup>7</sup> / <sub>8</sub> " | 2 <sup>7</sup> / <sub>8</sub> " | 2 <sup>15</sup> / <sub>16</sub> " |
|          | 120Vac MOTOR        | 7/8" | 1 <sup>13</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>13</sup> / <sub>16</sub> " | 1 <sup>9</sup> / <sub>16</sub> " | 1 <sup>13</sup> / <sub>16</sub> " | 2 <sup>7</sup> / <sub>8</sub> " | 2 <sup>7</sup> / <sub>8</sub> " | 2 <sup>15</sup> / <sub>16</sub> " |

# **BANDALUX**